Wideband, DC Pass Directional Coupler zudc20-5R23-S+

20dB Up to 50W 0.5 to 2 GHz 50Ω

The Big Deal

- Wideband, 0.5 to 2 GHz
- Power Handling up to 50W



CASE STYLE: HT2446-2

Product Overview

The Mini-Circuits ZUDC20-5R23-S+ wideband directional coupler offers exceptional performance operating over 0.5 to 2 GHz. This coupler has excellent coupling flatness, good directivity, and power handling. It is ideal for lab testing applications as well as for power monitoring over wide bands, among other applications.

Key Features

| Feature | Advantages | | |
|---|--|--|--|
| Wide bandwidth | With a bandwidth spanning 0.5 to 2 GHz, ZUDC20-5R23-S+ coupler is ideal for most lab testing applications, avoiding the need to switch components for different frequency bands. | | |
| Excellent Directivity • 30 dB typ. up to 2 GHz | High directivity allows sampling of input powers with minimal detrimental effects due to output mismatches. | | |
| Excellent Return Loss (In & Out) • 30 dB typ. up to 2 GHz | Good return loss over 0.5 to 2 GHz minimizes undesired reflections and resulting amplitude ripple. | | |

A. Performance and quality attributes and conditions not expressly stated in this specification document are intended to be excluded and do not form a part of this specification document.

B. Electrical specifications and performance data contained in this specification document are based on Mini-Circuit's applicable established test performance criteria and measurement instructions.

C. The parts covered by this specification document are subject to Mini-Circuits standard limited warranty and terms and conditions (collectively, "Standard Terms"); Purchasers of this part are entitled to the rights and benefits contained therein. For a full statement of the Standard Terms and the exclusive rights and remedies thereunder, please visit Mini-Circuits' website at www.ninicircuits.com/MCLStore/terms.jsp

Wideband, DC Pass

Directional Coupler

ZUDC20-5R23-S+

 50Ω

Up to 50W 20dB

0.5 to 2 GHz

Maximum Ratings


| Operating Temperature | -55°C to 100°C |
|-----------------------|----------------|
| Storage Temperature | -55°C to 100°C |
| Supplied Termination* | 1 W |
| DC Current | 1A |
| | |

Permanent damage may occur if any of these limits are exceeded up to 25°C, derates linearly to 325mW at 100°C.

Coaxial Connections

| INPUT | IN |
|----------------------------|-----|
| OUTPUT | OUT |
| COUPLED | CPL |
| TERMINATION (50Ω) INCLUDED | _ |

Outline Drawing



Features

- Wide frequency range, 0.5 to 2 GHz
- Good coupling flatness, ±0.5 dB typ.
- Excellent directivity, 30 dB typ. up to 2 GHz
- Excellent return loss, 30 dB typ. up to 2 GHz
- DC current pass through input to output

Applications

- · fixed satellite
- lab use
- GPS
- radar
- radio

- mobile

Generic photo used for illustration purposes only CASE STYLE: HT2446-2

Connectors Model **SMA Female** ZUDC20-5R23-S+


+ROHS Compliant
The +Suffix identifies RoHS Compliance. See our web site for RoHS Compliance methodologies and qualifications

Electrical Specifications at 25°C

| Parameter | Frequency (GHz) | Min. | Тур. | Max. | Units |
|----------------------------|-----------------|------|--------|-------|-------|
| Operating Frequency | | 0.5 | | 2 | GHz |
| Coupling | 0.5-2 | - | 20±1.0 | - | dB |
| Coupling Flatness (±) | 0.5-2 | - | ±0.5 | ±1.25 | dB |
| Mainline Loss ¹ | 0.5-2 | - | 0.19 | 0.4 | dB |
| Directivity | 0.5-2 | 23 | 35 | - | dB |
| Return Loss (In & Out) | 0.5-2 | 20.8 | 36 | - | dB |
| Return Loss (Coupling) | 0.5-2 | 20.8 | 35 | - | dB |
| Input Power ² | 0.5-2 | - | - | 50 | W |

- 1. Mainline loss includes coupling loss
- 2. Up to 25°C, derates linearly to 5W at 100°C.

Electrical Schematic





Typical Performance Data

| Francisco Maintina Land Counting Disastinity Deturn Land | | | | | | | |
|--|----------------------------------|----------------------------|---------------------|-------|----------------------------|-------|--|
| Frequency (MHz) | Mainline Loss¹ (dB) In-Out | Coupling (dB) In-Cpl | Directivity (dB) | In | Return Loss (dB) Out | Cpl | |
| 500 | 0.12 | 20.07 | 38.58 | 50.45 | 58.88 | 37.59 | |
| 600 | 0.14 | 19.51 | 40.22 | 46.77 | 47.54 | 39.76 | |
| 700 | 0.16 | 19.36 | 43.17 | 42.36 | 41.64 | 45.49 | |
| 800 | 0.16 | 19.50 | 49.31 | 39.62 | 39.14 | 60.72 | |
| 900 | 0.17 | 19.82 | 44.10 | 37.51 | 37.17 | 43.55 | |
| 1000 | 0.18 | 20.18 | 38.10 | 36.34 | 36.81 | 38.23 | |
| 1100 | 0.18 | 20.40 | 33.70 | 37.09 | 37.93 | 35.86 | |
| 1200 | 0.19 | 20.37 | 31.27 | 38.58 | 40.70 | 34.48 | |
| 1400 | 0.21 | 19.80 | 30.67 | 47.66 | 43.42 | 34.44 | |
| 1600 | 0.23 | 19.37 | 34.25 | 34.31 | 32.83 | 34.84 | |
| 1800 | 0.24 | 19.62 | 37.74 | 30.41 | 29.60 | 31.59 | |
| 2000 | 0.25 | 20.29 | 29.96 | 30.59 | 30.14 | 28.75 | |

1. Mainline loss includes coupling loss







- A. Performance and quality attributes and conditions not expressly stated in this specification document are intended to be excluded and do not form a part of this specification document.

 B. Electrical specifications and performance data contained in this specification document are based on Mini-Circuit's applicable established test performance criteria and measurement instructions.

 C. The parts covered by this specification document are subject to Mini-Circuits standard limited warranty and terms and conditions (collectively, "Standard Terms"); Purchasers of this part are entitled to the rights and benefits contained therein. For a full statement of the Standard Terms and the exclusive rights and remedies thereunder, please visit Mini-Circuits' website at www.minicircuits.com/MCLStore/terms.jsp